

Camera Control Unit

RMC-180



Quick Start Guide

Table of Contents

Warnings and Precautions	2
Warranty.....	3
Disposal	3
Packing List.....	4
Introduction	4
Features	4
Front Panel.....	5
Step by step to save camera position.....	7
Menu Setup	7
Rear Panel	9
Firmware upgrade procedure	10
Service & Support	11



Warnings and Precautions

1. Read all of these warnings and save them for later reference.
2. Follow all warnings and instructions marked on this unit.
3. Unplug this unit from the wall outlet before cleaning. Do not use liquid or aerosol cleaners. Use a damp cloth for cleaning.
4. Do not use this unit in or near water.
5. Do not place this unit on an unstable cart, stand, or table. The unit may fall, causing serious damage.
6. Slots and openings on the cabinet top, back, and bottom are provided for ventilation. To ensure safe and reliable operation of this unit, and to protect it from overheating, do not block or cover these openings. Do not place this unit on a bed, sofa, rug, or similar surface, as the ventilation openings on the bottom of the cabinet will be blocked. This unit should never be placed near or over a heat register or radiator. This unit should not be placed in a built-in installation unless proper ventilation is provided.
7. This product should only be operated from the type of power source indicated on the marking label of the AC adapter. If you are not sure of the type of power available, consult your Datavideo dealer or your local power company.
8. Do not allow anything to rest on the power cord. Do not locate this unit where the power cord will be walked on, rolled over, or otherwise stressed.
9. If an extension cord must be used with this unit, make sure that the total of the ampere ratings on the products plugged into the extension cord do not exceed the extension cord's rating.
10. Make sure that the total amperes of all the units that are plugged into a single wall outlet do not exceed 15 amperes.
11. Never push objects of any kind into this unit through the cabinet ventilation slots, as they may touch dangerous voltage points or short out parts that could result in risk of fire or electric shock. Never spill liquid of any kind onto or into this unit.
12. Except as specifically explained elsewhere in this manual, do not attempt to service this product yourself. Opening or removing covers that are marked "Do Not Remove" may expose you to dangerous voltage points or other risks, and will void your warranty. Refer all service issues to qualified service personnel.
13. Unplug this product from the wall outlet and refer to qualified service personnel under the following conditions:
 - a. When the power cord is damaged or frayed;
 - b. When liquid has spilled into the unit;
 - c. When the product has been exposed to rain or water;
 - d. When the product does not operate normally under normal operating conditions. Adjust only those controls that are covered by the operating instructions in this manual; improper adjustment of other controls may result in damage to the unit and may often require extensive work by a qualified technician to restore the unit to normal operation;
 - e. When the product has been dropped or the cabinet has been damaged;
 - f. When the product exhibits a distinct change in performance, indicating a need for service.

Warranty

Datavideo warrants that the equipment it manufactures shall be free from defects in material and workmanship for a period of 12 months from the date of product purchased. If equipment fails due to such defects, Datavideo will, at its option, repair or provide a replacement for the defective part or product.

Equipment that fails after the warranty period, has been operated or installed in a manner other than that specified by Datavideo, or has been subjected to abuse or modification, will be repaired for time and material charges at the Buyer's expense.

This warranty does not affect your statutory rights within the Country of purchase.

Disposal

For EU Customers only - WEEE Marking.



This symbol on the product indicates that it will not be treated as household waste. It must be handed over to the applicable take-back scheme for the recycling of electrical and electronic equipment. For more detailed information about the recycling of this product, please contact your local Datavideo office.

Packing List

1	x	USB cable USB A-USB A L:1.8M
1	x	Switching adaptor DC 12V / 0.5A
1	x	RMC-180 Instruction Manual

Introduction


The RMC-180 is special designed for remote controlling Datavideo PTC-100 HD/SD PTZ camera with the video calibration functions with it. One of RMC-180 can connect up to four of PTC-100 by Ethernet connection and up to 1,000 Meter distance away. To combine the Datavideo HD Switcher SE-2000 will be a turn key and affordable HD multi-Camera system for the application of big conference, church and surveillance market.

* RMC-180 supports Pelco protocol:


Features

- Connects up to four of Datavideo PTC-100 HD/SD PTZ camera
- Pan-Tile-Zoom control by Joystick
- Remote calibrates the Iris, Focus, Gain, and more
- Presetting the PTZ and video calibration up to four camera
- RS-422 remote control protocol by RJ-45 connector can connect camera up to 1,000 meter away.
- Tally input interface is fully compatible with Datavideo tally connection standard
- Small side can mount on the studio table with switcher

Front Panel



- | | |
|----------------------------|-----------------|
| 1. Focus | 7. Lock |
| 2. STR | 8. Speed |
| 3. CH A~D (Group Select) | 9. MENU |
| 4. IRIS | 10. LCD Monitor |
| 5. Ch A~D (Channel Select) | 11. Selectors |
| 6. Controller | 12. Mode Select |



FOCUS

Controls camera focus is controlled by the rotary knob.

When the MANUAL switch LED light on, the camera focus is by manual setting.



STR

STR switch is save the camera position.



Channel group A, B, C, D


Channel switch is select the save group CH A~CH D.



IRIS

Controls camera IRIS is controlled by the rotary knob.

When the MANUAL switch LED light on, the camera IRIS is by manual setting.



Channel Buttons

Channel buttons is save the camera position.

See page.7 for more details.



Control

The joystick is used in conjunction with several features. It is used to adjust the PAN, TILT, ZOOM settings of the video camera.

When the LOCK switch LED light on, the joystick function disable.



Speed

Three different modes for joystick control speed.



Menu

Menu button is setting the RMC-180 functions configuration.



LCD Display

The status of the RMC-180 is displayed within the LCD Display.



Selectors

Menu button is setting the RMC-180 functions configuration.



Mode Select

MODE – Color bar


A,B – Save MODE A or MODE B


ATW – Automatically white balance

Step by step to save camera position


1. Select group on CH A or CH B or CH C or CH D.



2. Push STR button , at same time you selected group will light on.



3. Push 1 of 4 light on button to save the camera position.



Menu Setup

FN00: Exit

Exit the menu setup mode.

FN01: Joystick Sens

Setting the joystick controls sensitivity.

FN02: Control Dir

PAN Direction Set-

Setting the camera PAN direction control is normal or reversed (LEFT / RIGHT).

TILT Direction Set-

Setting the camera TILT direction control is normal or reversed (UP / DOWN).

ZOOM Direction Set-

Setting the camera ZOOM direction control is normal or reversed (ZOOM IN / ZOOM OUT).

FOCUS Direction Set-

Setting the camera FOCUS direction control is normal or reversed (LEFT / RIGHT).

IRIS Direction Set-

Setting the camera IRIS direction control is normal or reversed (LEFT / RIGHT).

FN03: Shutter Set

Setting the camera shutter speed.

FN04: Mirror Set

Setting the camera display is normal or reversed (horizontal or rotate).

FN05: On Screen Disp

Setting the camera OSD On / Off (from RMC-180 output).

FN06: Gain Adjust

Setting the camera gain.

FN07: R/B Adjust

Setting the camera Red-gain, Blue-gain.

FN08: Power On/Off

Setting the camera power ON / OFF.

FN09: Video Format

Setting the camera video output format.

FN10: RMC-180 FW Ver-

Display the RMC-180 firmware version.


FN11: PTC-100 FW Ver-

Display the PTC-100 firmware version.

FN12: Camera Info

Display the camera information.

Rear Panel



1. Firmware Upgrade
2. RJ-45 Connect (To PTC-100)
3. Tally Input
4. Power input 12V 0.5A
5. Power On / Off switch



Firmware Upgrade

USB connect to computer for firmware upgrade.



Camera connect (RJ-45)

4 RJ-45 ports connect to camera.



Tally Input

Send in red color tally signal to tally LED. Red means on-air.



DC In Socket

Connect the supplied 12V 0.5A PSU to this socket. The connection can be secured by screwing the outer fastening ring of the DC In plug to the socket.




Power On/Off Switch

Switches the power On / Off


Firmware upgrade procedure



1. Connect the RMC-180 USB port to the computer.
2. Push in all four ticked buttons at the same time and hold in whilst powering ON the RMC-180.




3. RMC-180 LCD will display as below:



4. "RMC-180_U38" will display on the computer monitor.



5. Enter the "RMC-180_U38", and then delete "bootcode.bin" file within it.



6. Unzip and Paste the new firmware bin file in to the same place on the computer.
7. Power cycle, the RMC-180 and the unit should be ready for PTC-100 operation.

Service & Support

It is our goal to make your products ownership a satisfying experience. Our supporting staff is available to assist you in setting up and operating your system. Please refer to our web site www.datavideo-tek.com for answers to common questions, support requests or contact your local office below.

Datavideo Global Website: www.datavideo-tek.com

Datavideo Corporation

Tel: +1 562 696 2324	Fax: +1 562-698-6930	E-Mail: contactus@datavideo.us
----------------------	----------------------	--

Datavideo Technologies Europe BV

Tel: +31-30-261-96-56	Fax: +31-30 261-96-57	E-Mail: service@datavideo.nl
-----------------------	-----------------------	--

Datavideo UK Limited

Tel: +44 1457 851 000	Fax: +44 1457 850 964	E-Mail: sales@datavideo.co.uk
-----------------------	-----------------------	--

Datavideo Technologies Co., Ltd

Tel: +886 2 8227 2888	Fax: +886-2-8227-2777	E-mail: service@datavideo.com.tw
-----------------------	-----------------------	--

Datavideo Technologies China Co., Ltd

Tel: +86 21-5603 6599	Fax: +86 21-5603 6770	E-mail: service@datavideo.cn
-----------------------	-----------------------	--

Datavideo Technologies (S) PTE LTD

Tel: +65-6749 6866	Fax: +65-6749 3266	E-mail: service@datavideo.sg
--------------------	--------------------	--

Datavideo HK Limited.

Tel: +852 2833 1981	Fax: +852-2833-9916	E-mail: info@datavideo.com.hk
---------------------	---------------------	--

Datavideo France

Tel: +33 1 60 37 02 46	Fax: +33 1 60 37 67 32	E-Mail: info@datavideo.fr
------------------------	------------------------	--

Datavideo India

Tel: +91 120 4309120	Fax: +91 120 4309121	E-Mail: sales@datavideo.in
----------------------	----------------------	--

All the trademarks are the properties of their respective owners.
Datavideo Technologies Co., Ltd. All rights reserved 2018

G082060542B2