

BenchTek The Quiet Connection

DXA-6

Dual Phantom Power Adapter

Superb Sound
Plus Regulated
Phantom Power!



Can be handheld
or tripod mounted



Sounds Great

Now, an XLR adapter and phantom power unit in one compact device. Has all the great features of our popular DXA-4 adapters with the addition of 48 volt phantom power on both channels, for use with professional condenser microphones. Works with any stereo camcorder

DXA-6 Features

- Two balanced XLR inputs for stereo recording
- Dual 48 volt phantom power supplies for professional mics
- Auxiliary mini-jack on right channel for wireless mics
- Dual MIC/LINE level switches for versatility
- Dual drift free trim controls for reliable operation
- MONO/STEREO switch for single input recording
- Low noise transformers for superb sound
- Uses one standard 9 volt battery
- LED battery power indicator



Front Control Panel



Rear Connection Panel

Specifications

Input	: two transformer balanced XLR connectors auxiliary unbalanced mini-jack for right input	Battery Type	: one standard 9 volt alkaline battery : LED battery indicator
Output	: unbalanced stereo right angle mini-plug	Battery Duration	: 4 hours continuous use-typical
Input Level	: MIC setting: -60dBu : LINE setting: -10dBu	Case	: aluminum
Output Level	: mic level	Case Finish	: flat black
Attenuator	: adjustable from unity to zero output in 10 steps	Dimensions	: 5.25" L x 3.5" W x 1.25" H
Phantom Power	: dual regulated 48 volt power supplies current to 14 mA (direct short)	Weight	: 16 oz.

For equipment compatibility, prices and availability, call or visit our web site today.



BeachTek